



This reference guide describes useful information when using the satellite PTT transceivers.

1. Operating environment

- Move away from buildings and use the transceiver in areas with an open sky.
- Extended your arm horizontally, and raise your thumb.
- Turn your body around 360 degrees with your arm extended. Make sure that there are no obstacles such as buildings or trees higher than about 8 degrees.




① Receiving and transmitting may fail, depending on the satellite positions or nearby obstacles.



2. Checking the signal strength


- Turn ON the transceiver and wait for the registration to complete, which takes approximately 30 seconds.
- Confirm the antenna icon, indicating a connection with a satellite is established. After this, the registration has been completed, you can see your Talkgroup and the transceiver's name on the display.
- The status "IDLE" is displayed when the transceiver is ready to operate.

① While registering the transceiver, keep the antenna pointing to the sky. Otherwise, you may lose the signal from the satellite, and registration may fail.



3. Antenna position

- Hold the transceiver with its antenna straight up and pointing to the sky.
- If you hold the transceiver with a chest harness, make sure the antenna is pointing to the sky. Otherwise, you may lose the signal from the satellite.
- When you transmit and hold the transceiver in your hand, always keep it in front of your face.
 - ① Hold the transceiver above your shoulders and vertical while receiving and transmitting.




① When using the transceiver and the chest harness, we highly recommend that you use with our speaker microphone.



4. Distance with the other satellite PTT transceivers

Keep a minimum of 1.5 m (4.9 feet) away from other transceivers. Using within a closer range may cause interference.



5. Receiving


- Hold the transceiver with its antenna pointing to the sky.
- You cannot transmit while receiving signals in the same Talkgroup.
- When receiving is finished, the transceiver sounds a “Pi” beep, and displays the “OPEN” status.
 - ① If you hold down [PTT] while receiving signals, the transceiver sounds a “PiPiPiPiPi” beep, and displays “BUSY.”

6. Transmitting

- Wait until the Talkgroup becomes clear.
- While holding down [PTT], speak into the microphone at your normal voice level.
- Release [PTT] to receive.

To maximize the readability of your signal:

1. After holding down [PTT], pause briefly before you start speaking.
 2. Hold the microphone 5 to 10 cm (2 to 4 inches) from your mouth, and then speak at your normal voice level.
 - ① When you speak into the microphone, do not cover the mic hole in the front panel.
- Keep the communication ideally within 20 seconds.
 - ① This transceiver has a Time Out Timer function, which automatically stops transmissions that exceed 40 seconds. If you need to transmit further, release [PTT], and then hold down [PTT] again.
 - If the connection becomes poor while transmitting, the transceiver sounds a “PuPu” beep at 1.5 second intervals. Confirm that the antenna is pointing to the sky, or attempt to relocate your operating location if the signal condition does not improve.




NOTE:

- An initial transmission may take up to 2 seconds to authenticate. After this, the service will perform normally. Continue to hold down [PTT] for several seconds before you begin speaking. This prevents some audio from being cut off at the beginning of transmission.
- If the transceiver displays “OPEN” on the display, you can start to transmit.
 - ① Before transmission, always confirm the “OPEN” status on the display.

7. Carrying a transceiver

- When you carry the transceiver in your hand, keep the antenna pointing to the sky.
- When using a chest harness, keep the transceiver above your shoulders, and vertical while carrying.



Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand, and/or other countries.
All other products or brands are registered trademarks or trademarks of their respective holders.